

## NewHank MP103MKII RS-232 Remote control

Baud Rate 9600bps  
Data Size 8bit  
Stop bit 1

Complete command string: 0x55, 0x03, 0x01, <cmd>, 0xFF  
Example 1 command: 0x55, 0x03, 0x01, 0x4C, 0xFF  
Example Up command: 0x55, 0x03, 0x01, 0x46, 0xFF

1 = 0x4C  
2 = 0x0E  
3 = 0x4D  
4 = 0x0F  
5 = 0x4F  
6 = 0x4E  
7 = 0x0B  
8 = 0x4B  
9 = 0x4A  
010 = 0x48  
LoopIn = 0x14  
LoopOut = 0x43  
AutoCue = 0x07  
Back = 0x0C  
Cue = 0x50  
Down = 0x16  
Eject = 0x17  
Enter = 0x52  
Exit = 0x42  
Left = 0x47  
MasterTempo = 0x5F  
Mute = 0x1F  
Next = 0x01  
PauzePlay = 0x13  
Pitch = 0x08  
PitchMin = 0x09  
PitchPlus = 0x06  
Previous = 0x41  
Program = 0x10  
ReturnPauze = 0x04  
ReturnPlay = 0x44  
Reloop = 0x56  
Repeat = 0x00  
Right = 0x15  
Single = 0x40  
Source = 0x0D  
Stop = 0x12  
Time = 0x57  
Up = 0x46